

Full HD Wireless Network Media Player

1080p Solid-State Wireless Network Media Player

NMP-570w



ViewSonic's new NMP570w full HD wireless media player provides extreme reliability and stunning 1080P video playback mixed with rich content harnessed live from the cloud. The NMP570w utilizes the latest technologies - HTML5 for delivering dynamic information at the point of service over the web or from a network server. Easy –to-use content management software – Signage Manager Express now offers expanded templates in both landscape and portrait supporting HTML5 "Smart Widgets" for multi-zone screen applications.

- Support for HTML5.
 MPEG 1/2/4, H.264 Video Decoding
 IEEE 802.3 Ethernet 10/100 Base-T with auto-MDIX
 Built-in Wireless 802:11 b/g/n
 Display Outputs: HDMI, VGA, dual output video
 Audio Output: Stereo line output
 Signage Manager Express software included
 Built-in Watch Dog Timer
 Applications:

 Transportation Signage
 Electronic Menu Boards
 Retail Advertisements
 Campus Communication
 - Trade Show Signage
 - Point-of-Sale Advertising



Full HD Wireless Network Media Player



Specifications				
OPERATING SYSTEM	Linux			
SUPPORTING PROTOCOLS	TCP/IP, HTTP			
INSTALLED SOFTWARE	W3C-SMIL 3.0, W3C-HTML5			
NETWORK MANAGEMENT	Signage Manager Express			
CONNECTORS	10/100 Ethernet, Mini 3.5mm, WiFi 802:11 b/g/n			
DISPLAY	HDMI, VGA, A/V			
AUDIO	3.5mm mini stereo port			
NETWORK	10/100 Ethernet			
USB	USB (x2)			
DECODING	Video MPEG-1, 2, 4; H.264, VC-1/WMV9			
	Audio MPEG-1 (layers 1 & 2), MP3			
STREAMING PROTOCOL	Types HTTP, local file playback			
RESOLUTIONS	640x480, 800x600, 1024x768, 1280x1024, 1280x768, 1366x768, 1920x1080			
IMAGE FILE	Formats JPEG, PNG			
LOCAL STORAGE	4GB flash memory CF card expansion slot			
SCANNING FORMAT	SDTV 480i, EDTV 480p, HDTV 720p, 1080i			
SCREEN ROTATION	Landscape, portrait (+90°, -90°)			
POWER	DC 12V (max), AC Adapter 12V DC 1.5A			
AUTO RESET	Automatic error recovery with built-in Watch Dog Time			
OPERATING CONDITIONS	Temperature 50°–104°F (0°–40°C)			
	Humidity 5–85% (non-condensing)			
DIMENSIONS (W x H x D) Physical	5.9" x 4.3" x 1.1" (150.8mm x 110mm x 28.6mm)			
WEIGHT	Net 0.76 lb. (0.35 kg)			
	Gross 3 lb. (1.4 kg)			
WALL MOUNT	MIS-D100			
REGULATIONS	FCC, FCC-ID, ICES003			



Media player, AC adapter, Ethernet cable, Quick Start Guide, User Guide on CD, Signage Manager Express CD

		- Contractor								
Avant teo lites 7/										
And Comparison (INVESTIGATION TAL	nage links Woger 80									
The second s										
a sea e X	Sec. 1	_								
Timek Territoria										
Alexandre										
The Trainer										
Stars.										
Average		_								
	ager Espress 3.0.4						_	_	No. of Lot of Lo	ł
					_	-			- Concert	
File(F) Ecit(E)	Player(P) Lenguage(L) Help									
		. 82	7							1
	· · · ·		1						-	ģ
	570w Weekly schedule	Export							Firetoware	1
NMP-560										
Schedule temp		Aspect ratio								
pand drive Fail to provide an element				-						
pand drive Fail to provide an element	Bakery Barry berry berry 1200			NON	TUE	WED	ТНИ	FRI	SAT	
pand drive Fail to provide an element	an Bakery		*		TUE	WED	THU	ŦĦJ	SAT	
pand drive Fail to provide an element	late Bakery Deerg specieltarti it 1500 Oper Jourt	- Add	*		TUE	WED	THU	ŦRI	SAT	
pand drive Fail to provide an element	late Bakery Serring sector tract at 1950 Open hours Non to Fin (State to 21.00 Sum Set (State to 20.00	- 00.00	*		TUE	WED	ТНО	ŦŧĠ	SAT	
pand drive Fail to provide an element	late Bakery Deeng speciatures at 1800 Open Nours Monito Fr 6000 to 21.00	- 00.00 00.00	*		TUE	WED	THU	ŦRI	SAT	
pand drive Fail to provide an element	Nate Bakery Benny spore med at 1500 Open hours More 16 foto to 2100 Sur Ser 1000 to 2100 Sur Ser 1000 to 2000	- 08.00 01.00 02.00	*		TUE	WED	THU	ŦRI	SAT	
pand drive Fail to provide an element	Ante Bakery Deenseur sees in 1900 Geenseur Moris Mickolo is 21.00 En die 1000 is 2000 FastFood	- 06.00 01:00 02:00 03:00	*		TUE	WED	THU	H	SAT	
pand drive Fail to provide an element	Nate Bakery Benny spore med at 1500 Open hours More 16 foto to 2100 Sur Ser 1000 to 2100 Sur Ser 1000 to 2000	*	*		TUE	WED	THU	TRU	SAT	
pand drive Fail to provide an element	lait Backeny Backeng secar serie it 2100 Open tears Marce 16 c630 vo21:00 Marce 16 c630 vo21:00 Marce 10 c63	* • Add - 06.00 02.00 02.00 03.00 04.00 05.00 06.00	*		TUE	WED	THU	ŦĦS	SAT	
pand drive Fail to provide an element	Inter Backery Description frame of 1500 Very to 45 de 050 up 21.00 To 500 LOOD WORKS Frankling 650 up 3100 Coart in mini-varget Frond Court	*	*		TUE	WED	THU	ŦR	SAT	
pand drive Fail to provide an element	Autr	 Add 06.00 02.00 03.00 04.00 05.00 06.00 06.00 06.00 06.00 	*		TUE	WED	ТНО	H	TA2	
pand drive Fail to provide an element	Anter Backery Descriptions for the M 1500 Vorus to A for door up 2100 To the S to A to		*		TUE	WED	ТНО	H	SAT	
pand drive Fail to provide an element	Autr	 	*		TUE	WEC	THU	Ħ	TA2	
pand drive Fail to provide an element	And the second s	* 4.4d - 06.00 01.00 02.00 03.00 05.00	*		TUE	WED	THU	Ħ	5AT	
pand drive Fail to provide an element	Anter Backery Descriptions for the M 1500 Vorus to A for door up 2100 To the S to A to	Add Add Consol C	*		TUE	WED	THU	ŦR	5AT	
	Butter Date pay Derror parameters in 2100 Derror parameters in 2100 Derror parameters in 2100 Derror parameters in 2100 Parameters in 200 Description and 200 Shoopping Mall		*		TUE	WED	THU	FRG	JAT .	
	And the second s		*		TUE	WED	THU	H	TAL	
	And the second s	Add A	*		TUE	WEC	THU	H	TAL	
	And the second s		*		TUE	WED	Тни	H	λ.	
	And the second s	Add A	*		TUE	WED	Тни	H	τά	



*Power savings may vary based on actual usage and other factors. Programs, specifications and availability are subject to change without notice. Selections, offers and programs may vary by country; see your ViewSonic representative for complete details. Corporate names, trademarks stated herein are the property of their respective companies. Copyright © 2012 ViewSonic Corporation. All rights reserved. [16013-01B-0412] NMP570W